

Electrical Network Analyzer



2726 NA

FEATURES

- Microprocessor-controlled
- Built-in earth tester
- Built-in loop/psc tester. 0.03-2000Ω (software ctrl)
- Built-in voltmeter
- Built-in wiring checker
- Single button, smart-push operation for all functions
- Displays L-N and L-E voltages. 50 to 280Vac (sine)
- Displays Line path impedance. 0.01-2000Ω (software ctrl)
- Displays Earth path impedance. 0.01-2000Ω (software ctrl)
- Displays Neutral path impedance. 0.01-2000Ω (software ctrl)
- Displays psc line to Neutral. 6kA@230Vac supply
- Displays psc line to Earth. 6kA@230Vac supply
- Re-scroll through previous results
- Bat. ok/low battery indicator
- Auto-off function
- Color coded test leads
- Rugged Case
- Ultra low power consumption

SPECIFICATIONS

Loop / Earth / Wires	0.03-2000Ω (auto-ranging)
Prospective short circuit	0~6kA at 230Vac
Operating voltage	50V~275Vac (50Hz)
Best performance at rated voltage	230Vac ± 20V Max.10A
Accuracy of voltage	±1% (210~250V) ±3% otherwise
Accuracy of loops / earth	±2% (0.05~50Ω) / ±3% (50~500Ω)
Accuracy of wires impedances	±15% (above 500Ω)
Operating-temperature -humidity	0°C to 40°C 80% Maximum
Dimensions	205(L) × 90(W) × 55(D)mm
Weight (battery included)	Approx. 570g
Power source	1.5V (AA) × 6
Safety standard	EN 61010-1 CAT IV 300V EN 61326-1
Accessories	Instruction manual Test leads Carry case Batteries

The 2726 NA is a portable electrical network analyzer. It has a built-in Earth tester which does not require the use of poles or long wires. This instrument is useful for fault-finding or commissioning of electrical installations. Differentiation between the Line (hot), Neutral and Earth (ground) paths by reading their values has never been so easy. Bad contacts, old wiring or bad earth paths are quickly identified. Faulty electrical networks can be resolved in a fraction of the time normally required using conventional equipment, as faults can be identified and diagnosed quickly. With the 2726 NA, the user can determine which wire needs to be attended to and why. For example, old wires with high impedance can be found and replaced before a fire starts. The complete electrical network can be analyzed by scrolling through the results. The 2726 NA includes a built-in loop impedance and prospective short circuit tester as well as a voltmeter.

