

Analogue Portable Instrument



ST-2000

AC/DC Ammeter & Voltmeter are moving coil or Rectifier instrument.

Name	Range	No.	
AC Ammeter	2 Ranges	20/100mA	1301
		50/100mA	1302
		100/500mA	1303
		0.2/1A	1304
		0.5/1A	1305
		1/5A	1306
		2/10A	1307
		5/25A	1308
		10/30A	1309
		5/30A	1322
	3 Ranges	20/100/500mA	1310
		100/500/1000mA	1311
		0.2/0.5/1A	1312
		0.5/1/2A	1313
		2/5/10A	1314
4 Ranges	5/10/20A	1315	
	20/50/100/200mA	1316	
	0.1/0.2/0.5/1A	1317	
	0.5/1/2.5/5A	1318	
	2/5/10/20A	1319	
10/30/100/300mA	1321		
AC Voltmeter	2 Ranges	15/30V	1501
		30/75V	1502
		75/150V	1503
		150/300V	1504
		300/750V	1505
	3 Ranges	75/150/300V	1506
		150/300/600V	1507
		150/300/750V	1508

- Principle : Moving coil type
- Accuracy : $\pm 0.5\%$ F.S.
- Scale Length : Approx. 135mm(5-3/8")
- Weight : Approx. 1.7kg
- Dimension : 196(L) \times 170(W) \times 87(D)mm
- Case Material : Bakelite with glass window

Name	Range	No.	
DC Ammeter	2 Ranges	100/500 μ A	1404
		500/1000 μ A	1405
		10/50mA	1406
		50/100mA	1407
		50/500mA	1408
		10/30/100mA	1409
		0.1/0.3/1A	1410
		1/3/10A	1411
	3 Ranges	3/10/30A	1412
		0.1/0.3/1/3mA	1414
		1/3/10/30mA	1415
		10/30/100/300mA	1416
		0.1/0.3/1/3A	1417
		1/3/10/30A	1418
		30/100/300/1000mA	1419
DC Voltmeter	1 Range	50mV	1601
	2 Ranges	5/10V	1602
		1/3V	1603
		10/30V	1604
		30/100V	1605
		30/150V	1606
		100/300V	1607
		300/1000V	1608
		1/3/10V	1610
	3 Ranges	3/10/30V	1611
		30/100/300V	1612
		3/10/30/100V	1614
	4 Ranges	1/3/10/30V	1615
		10/30/100/300V	1616
		30/100/300/1000V	1617

Special ranges are available upon request.